LM741

## Electrical Characteristics (Note 5) (Continued)

Note 3: For operation at elevated temperatures, these devices must be derated based on thermal resistance, and  $T_j$  max. (listed under "Absolute Maximum Ratings").  $T_j = T_A + (\theta_{jA} P_D)$ .

Thermal Resistance	Cerdip (J)	DIP (N)	HO8 (H)	SO-8 (M)
$\theta_{jA}$ (Junction to Ambient)	100°C/W	100°C/W	170°C/W	195°C/W
$\theta_{jC}$ (Junction to Case)	N/A	N/A	25°C/W	N/A

Note 4: For supply voltages less than ±15V, the absolute maximum input voltage is equal to the supply voltage.

Note 5: Unless otherwise specified, these specifications apply for  $V_S = \pm 15V$ ,  $-55^{\circ}C \le T_A \le +125^{\circ}C$  (LM741/LM741A). For the LM741C/LM741E, these specifications are limited to  $0^{\circ}C \le T_A \le +70^{\circ}C$ .

Note 6: Calculated value from: BW (MHz) = 0.35/Rise Time( $\mu$ s).

Note 7: For military specifications see RETS741X for LM741 and RETS741AX for LM741A.

Note 8: Human body model, 1.5 k $\Omega$  in series with 100 pF.

## **Schematic Diagram**

